



Tech Info Library

Apple III: Printer Driver Data Configuration Block

Revised: 1/17/85
Security: Everyone

Apple III: Printer Driver Data Configuration Block

=====

NOTE: All values are in hexadecimal.

| | 0 | 1 | 2 | 3 | 4 |
|------------|----|---|---|---|---|
| Baud rate: | | | | | |
| 110 | 03 | | | | |
| 134.5 | 04 | | | | |
| 300 | 06 | | | | |
| 600 | 07 | | | | |
| 1200 | 08 | | | | |
| 1800 | 09 | | | | |
| 2400 | 0A | | | | |
| 4800 | 0C | | | | |
| 9600 | 0E | | | | |

| | |
|---------------------|----|
| Data format: | |
| 7 data/odd parity | 22 |
| 7 data/even parity | 26 |
| 7 data/mark parity | 2A |
| 7 data/space parity | 2E |
| 8 data/no parity | 00 |
| 6 data/odd parity | 42 |
| 6 data/even parity | 46 |
| 6 data/mark parity | 4A |
| 6 data/space parity | 4E |

Delay after CR:

*

Delay after LF:

*

Delay after FF:

*

| | | | | |
|---|---|---|---|---|
| 0 | 1 | 2 | 3 | 4 |
|---|---|---|---|---|

* In character times; may be any value from \$00 to \$FF.

Apple Technical Communications

Tech Info Library Article Number:1048